



POWERTIP TECH. CORP.
DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

Specification For Approval

【產品規格書】

Customer : RYSTON

Model Type : LCD Module

Sample Code : _____

Mass Production Code : PC2004ERF-BWB-B

Edition : 0

| Customer Sign | Sales Sign | Approved By | Prepared By |
|---------------|------------|---------------------------|--------------|
| | | 曾 牙 輝 成 11/13-01 | 熊小英 11/13-01 |

CONTENTS

1. SPECIFICATIONS

- 1.1 Features
- 1.2 Mechanical Specifications
- 1.3 Absolute Maximum Ratings
- 1.4 DC Electrical Characteristics
- 1.5 Optical Characteristics
- 1.6 Backlight Characteristics

2. MODULE STRUCTURE

- 2.1 Counter Drawing
- 2.2 Interface Pin Description
- 2.3 Timing Characteristics
- 2.4 Display Command
- 2.5 Character Pattern



POWERTIP TECHNOLOGY CORPORATION

DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

1. SPECIFICATIONS

1.1 Features

- 20-characters, four-lines liquid crystal display of 5*7 dot matrix + cursor
- 1/16 Duty, 1/4 bias
- FSTN LCD, positive, White
- Transflective LCD
- 6 o'clock viewing angle
- 4 bits or 8 bits parallel data input
- Built-in EL backlight

1.2 Mechanical Specifications

- Outline dimension : 118.0mm(L)*43.0mm(W)*10.1mm max.(H)
- Viewing area : 76.0mm *25.2mm
- Active area : 70.4mm *20.8mm
- Dot size : 0.55mm *0.55mm
- Dot pitch : 0.6mm *0.6mm
- Character Size : 2.95mm *4.75mm

1.3 Absolute Maximum Ratings

| Item | Symbol | Conditions | Min. | Max. | Unit |
|--------------------------|--------|------------|----------|---------|------|
| Power supply Voltage | VDD | - | -0.3 | +0.7 | V |
| LCD drive Supply voltage | VDD-VO | - | VDD-10.0 | VDD+0.3 | V |
| Input voltage | VIN | - | -0.3 | VDD+0.3 | V |
| Operating temperature | TOPR | - | 0 | 50 | °C |
| Storage temperature | TSTG | - | -20 | 70 | °C |
| Humidity*1 | HD | - | - | 90 | %RH |

1.4 DC Electrical Characteristics

VDD=+5V±10%,VSS=0V,TA=25°C

| Item | Symbol | Condition | Min. | Typ. | Max. | Unit |
|----------------------|--------|-----------|--------|------|------|------|
| Logic Supply voltage | VDD | - | 4.5 | - | 5.5 | V |
| "H" input voltage | VIH | - | 0.7VDD | - | VDD | V |
| "L" input voltage | VIL | - | -0.3 | - | 0.6 | V |
| "H" output voltage | VOH | - | 3.9 | - | VDD | V |
| "L" output voltage | VOL | - | - | - | 0.4 | V |
| Supply current | IDD | VDD=5V | - | 1.5 | - | mA |
| LCD driving voltage | VOP | VDD-VO | - | 4.9 | - | V |



POWERTIP TECHNOLOGY CORPORATION

DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

1.5 Optical Characteristics

1/16 duty, 1/4 bias, $V_{op}=4.9V$, $T_a=25^{\circ}C$

| Item | Symbol | Conditions | Min. | Typ. | Max | Reference |
|---------------------|----------|--|--------------|--------|--------|-------------|
| Viewing angle | θ | $C \geq 2.0, \phi = 0^{\circ}$ | 30° | - | - | Notes 1 & 2 |
| Contrast | C | $\theta = 5^{\circ}, \phi = 0^{\circ}$ | - | 4 | - | Note 3 |
| Response time(rise) | t_r | $\theta = 5^{\circ}, \phi = 0^{\circ}$ | - | 120 ms | 180 ms | Note 4 |
| Response time(fall) | t_f | $\theta = 5^{\circ}, \phi = 0^{\circ}$ | - | 130 ms | 200 ms | Note 4 |


| Parameter | Symbol | Temperature ($^{\circ}C$) | Standard | | | Unit |
|-----------------------------|--------|-----------------------------|----------|-----|-----|------|
| | | | Min | Typ | Max | |
| Driving voltage VDD-VLCD | VOP | 0 | 4.5 | 4.8 | 5.1 | V |
| | | 25 | 4.3 | 4.8 | 5.0 | |
| | | 50 | 3.8 | 4.1 | 4.4 | |




POWERTIP TECHNOLOGY CORPORATION

DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

Note 1: Definition of angles θ and ϕ





Note 2: Definition of viewing angles θ_1 and θ_2



Note : Optimum viewing angle with the naked eye and viewing angle θ at C_{max} . Above are not always the same

Note 3: Definition of contrast C

$$C = \frac{\text{Brightness (reflection) of unselected dot (B2)}}{\text{Brightness (reflection) of selected dot (B1)}}$$



Note: Measured with a transmissive LCD panel which is displayed 1 cm^2

V_{OPR} : Operating voltage
 t_r : Response time (rise)

f_{FRM} : Frame frequency
 t_f : Response time (fall)



POWERTIP TECHNOLOGY CORPORATION

DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

1.6 Backlight Characteristic

The LCD Module is backlight using a EL panel

- Maximum ratings

| Item | Symbol | Maximum | Unit |
|-----------------------|--------|---------|------|
| Supply voltage | Vmax | 170 | Vrms |
| Supply frequency | Fmax | 1000 | Hz |
| Operating temperature | Topr | -35~+50 | °C |
| Operating humidity | Hopr | 90 | %RH. |
| Storage temperature | Tstg | -40~+60 | °C |
| Storage humidity | Hstg | 70 | %RH. |

- Using specification

| Item | Specification | Unit |
|-------------------|---------------|------|
| Operating voltage | 110 | Vrms |
| Frequency | 400 | Hz |

- Electrical Characteristics

| Item | | Condition | Unit | Min. | Typ | Max. |
|----------------------|---|------------|--------------------|--------|-----|------|
| Initiate intensity | | (sinewave) | cd/m ² | 48 | 60 | - |
| CIE color coordinate | X | VAC 110 | | 0.2997 | | |
| | Y | Vrms | | 0.3876 | | |
| Current density | | Freq 400 | mA/cm ² | 0.138 | | |
| Power density | | Hz | mW/cm ² | 2.98 | | |
| Color | | | White | | | |



2. MODULE STRUCTURE


2.1 Counter Drawing

*See Appendix

2.2 Interface Pin Description

| Pin No. | Symbol | Signal Description |
|---------|-----------|---|
| 1 | VSS | Signal ground (GND) |
| 2 | VDD | Power Supply (5 V) |
| 3 | VO | Operating voltage (LCD Driver) |
| 4 | RS | Register Selection input High = Data register Low = Instruction register (for write) Busy flag address counter (for read) |
| 5 | R/W | Read/Write signal input is used to select the read/write mode High = Read mode, Low = Write mode |
| 6 | E | Start enable signal to read or write the data |
| 7~10 | DB0 ~ DB3 | Four low order bi-directional three-state data bus lines. Use for data transfer between the MPU and the LCD module. These four are not used during 4-bit operation. |
| 11~14 | DB4 ~ DB7 | Four high order bi-directional three-state data bus lines. Used for data transfer between the MPU and the LCD module. DB7 can be used as a busy flag. |
| | A | Power supply LED backlight (+) |
| | K | Power supply LED backlight (-) |

Contrast Adjust




POWERTIP TECHNOLOGY CORPORATION


DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

2.3 Timing Characteristics

- Writing data from MPU to ST7066U



- Reading data from ST7066U to MPU



POWERTIP TECHNOLOGY CORPORATION

DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

• Write Mode (Writing data from MPU to ST7066U)

(V_{cc} = +5V, T_a = 25°C)

| Symbol | Characteristics | Test Condition | Min. | Typ. | Max. | Unit |
|---------------------------------|-------------------------|-----------------|------|------|------|------|
| T _C | Enable Cycle Time | Pin E | 1200 | - | - | ns |
| T _{PW} | Enable Pulse Width | Pin E | 140 | - | - | ns |
| T _R , T _F | Enable Rise / Fall Time | Pin E | - | - | 25 | ns |
| T _{AS} | Address Setup Time | Pins: RS, RW, E | 0 | - | - | ns |
| T _{AH} | Address Hold Time | Pins :RS, RW, E | 10 | - | - | ns |
| T _{DSW} | Data Setup Time | Pins: DB0~DB7 | 40 | - | - | ns |
| T _H | Data Hold Time | Pins: DB0~DB7 | 10 | - | - | ns |

• Read Mode (Reading data from ST7066U to MPU)

(V_{cc} = +5V, T_a = 25°C)

| Symbol | Characteristics | Test Condition | Min. | Typ. | Max. | Unit |
|---------------------------------|-------------------------|-----------------|------|------|------|------|
| T _C | Enable Cycle Time | Pin E | 1200 | - | - | ns |
| T _{PW} | Enable Pulse Width | Pin E | 140 | - | - | ns |
| T _R , T _F | Enable Rise / Fall Time | Pin E | - | - | 25 | ns |
| T _{AS} | Address Setup Time | Pins: RS, RW, E | 0 | - | - | ns |
| T _{AH} | Address Hold Time | Pins :RS, RW, E | 10 | - | - | ns |
| T _{DDR} | Data Setup Time | Pins: DB0~DB7 | - | - | 100 | ns |
| T _H | Data Hold Time | Pins: DB0~DB7 | 10 | - | - | ns |



POWERTIP TECHNOLOGY CORPORATION

DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

2.4 Display Command

| Instructions | Instruction Code | | | | | | | | | | Description | Execution Time (fosc=270KHZ) |
|----------------------------|------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|---|---------------------------------|
| | RS | R/W | DB7 | DB6 | DB5 | DB4 | DB3 | DB2 | DB1 | DB0 | | |
| Clear Display | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | Write "20H" to DDRAM. and set DDRAM address to "00H" from AC. | 1.52ms |
| Return Home | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | × | Set DDRAM address to "00H" from AC and return cursor to it's original position if shifted. The contents of DDRAM are not changed. | 1.52ms |
| Entry Mode Set | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | I/D | SH | Assign cursor moving direction and make shift of entire display enable. | 37 μ s |
| Display ON/OFF Control | 0 | 0 | 0 | 0 | 0 | 0 | 1 | D | C | B | Sets display (D), cursor(C), and blinking of cursor(B) on/off control bit. | 37 μ s |
| Cursor or Display Shift | 0 | 0 | 0 | 0 | 0 | 1 | S/C | R/L | × | × | Set cursor moving and display shift control bit, and the direction, without changing of DDRAM data. | 37 μ s |
| Function Set | 0 | 0 | 0 | 0 | 1 | DL | N | F | × | × | Set interface data length (DL:4-bit/8-bit), numbers of display line (N: 1-line/2-line), display font type(F:5*8 dots/5*11 dots) | 37 μ s |
| Set CGRAM Address | 0 | 0 | 0 | 1 | AC5 | AC4 | AC3 | AC2 | AC1 | AC0 | Set CGRAM address in address counter. | 37 μ s |
| Set DDRAM Address | 0 | 0 | 1 | AC6 | AC5 | AC4 | AC3 | AC2 | AC1 | AC0 | Set DDRAM address in address counter. | 37 μ s |
| Read Busy Flag and Address | 0 | 1 | BF | AC6 | AC5 | AC4 | AC3 | AC2 | AC1 | AC0 | Whether during internal operation or not can be known by reading BF. The contents of address counter can also be read. | 0 μ s |
| Write Data to RAM | 1 | 0 | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | Write data into internal RAM (DDRAM/CGRAM). | 37 μ s |
| Read Data from RAM | 1 | 1 | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | Read data from internal RAM (DDRAM/CGRAM). | 37 μ s |

※ "x":don't care



POWERTIP TECHNOLOGY CORPORATION



DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN

2.5 Character Pattern





POWERTIP TECHNOLOGY CORPORATION

DISPLAY DEVICES FOR BETTER ELECTRONIC DESIGN



| PIN NO. | SIGNAL |
|---------|--------|
| 1 | VSS |
| 2 | Vdd |
| 3 | Vo |
| 4 | RS |
| 5 | R/W |
| 6 | E |
| 7 | DB0 |
| 8 | DB1 |
| 9 | DB2 |
| 10 | DB3 |
| 11 | DB4 |
| 12 | DB5 |
| 13 | DB6 |
| 14 | DB7 |



The tolerance unless classified $\pm 0.3\text{mm}$

SCALE: 4/1



| | |
|-----------------------|------------------------|
| POWERTRIP TECHNOLOGY | |
| SCALE: 1/1 | MODEL NAME: PC 2004-B |
| UNIT: mm | TITLE: COUNTER DRAWING |
| EDI: PAGE: 1/1 | DRAWN NO. PC-95022 |
| APPROVED: [Signature] | CHECKER: [Signature] |
| DATE: 87.4.28 | PROGRAM: [Signature] |